








Antenna Cables

Coaxial Cable Assemblies

TECHNICAL DATA

	Model	Length	Dia. (in.)	Type	Loss (dB)	Connectors
	ARG2	2 ft.	.242	RG-8/X - Belden 9258	.25	BNC Straight
	ARG2RT	2 ft.	.110	RG174/U - Belden 8216	.50	BNC Right Angle
	ARG15	15 ft.	.242	RG-8/X - Belden 9258	1.4	BNC Straight
	ARG25	25 ft.	.405	RG-8/U - Belden 9913F7	1.9	BNC Straight
	ARG50	50 ft.	.405	RG-8/U - Belden 9913F7	2.8	BNC Straight
	ARG100	100 ft.	.405	RG-8/U - Belden 9913F7	4.6	BNC Straight
	ARX125 NOTE: Requires RF amplifier such as the UFM230	125 ft.	.242	RG-8/X - Belden 9258	12.5	BNC Straight

